

# PIR MOTION SENSOR & SOUND ACTIVATED LIGHT SWITCH

Product&amp;Family Code:

088 001 0004

**HL 483**
**GOLF**

**WHITE**

## Technical Data

Voltage	AC 220-240V / 50-60Hz
Detection Distance	6 ± 2 m Max. (<24°C)
Time-delay	Max. 5 sec ~ 10±2 min. (Adj)
Ambient Light	< 10Lux ~ 1000Lux
Average Load	Max 500W (~220V AC)
Protection Class	II
IP Rating	20
Sound Control Sensitivity:	30db ~ 90db (adjustable)
Material	Plastic
CE Approved	Yes

## Technical Drawing

## Applications

- For use indoors

## Features

- A passive infrared sensor (PIR sensor) is an electronic sensor that measures infrared (IR) light radiating from objects in its field of view.
- The wide detection range senses an up, down, left and right field of motion.
- It works by seeing human body heat in motion via infrared rays.
- The Sensor is susceptible to any sound.

